



---

# VRX-49C

## Audio/Video Receiver 4.9 GHz

---

This small receiver is definitely the best 4.9 GHz Video receiver on the market. Fully synthesized this receiver has an SMA connector for different type of antennas for 4.9 GHz. This receiver has 8 channels and it covers all frequencies in 4.9 GHz band. This small video receiver can access any video transmitter in 4.9 GHz band.



Technical Specifications	
FREQUENCY RANGE:	4,950-5,000 MHz
POWER SUPPLY	10 V– 14.4 V
CURRENT CONSUMPTION	380 mA
DEMODULATION	WFM
SENSITIVITY	-86 dBm
ANTENNA CONNECTOR	SMA
VIDEO INVERSE FUNCTION	N/A
VIDEO OUTPUT	1V
AUDIO OUTPUT	300 mV
POLARITY PROTECTED	YES
PLL (PHASE LOCKED LOOP)	YES
TEMPERATURE RANGE:	-20+70°C
NUMBER OF CHANNELS	8 preprogrammed channels
DIMENSIONS	6.5" X 4" X 2.1"